



## INTRODUCTION

AllsWell brings innovation to the infrared microphone system field, with its outstanding products. It is a leading designer and manufacturer of IR microphone systems from Taiwan that it has been marketing its products in the U.S and great Asia for several years. Our OEM & ODM services provide customers with complete guaranteed satisfaction. Our systems give reliable solutions to solve the challenges of weak audio equipments in the classroom and conference rooms.

**IRW-469**




**IRW-489**



IRW-489/469 sets are both the functional, medium-sized Infrared Wireless Microphone Systems. The main receiver (IRW-489 or 469) comes with four transmitters (handhelds or pendants), 2 sensors and 2 dual-slot charger stands. They both are the four-channel systems that they can be used broadly in every standard size room, especially for those in schools. On the front side, there are 4 volume control knobs, which can be easily adjusted by users. The only difference between them is IRW-489 receiver case is made of plastic, but metal one on IRW-469.

## **IRW-489/469 --- TECHNICAL SPECIFICATION**

Channel	FOUR Channel	Using Control:
Receiving Frequency	2.08/2.54 /2.3/2.8MHz	(1) Power ON/OFF Switch
Squelch	RF carrier / Tone control	(2) Channel A Volume
Power	12V DC / 0.5A	(3) Channel B Volume
Output	MIC : 80mv / 600ohm	(4) Channel C Volume
	LINE: 320mv / 10k ohm	(5) Channel D Volume
Inputs/Outputs	-2.1mm plug-in type input power jack -RCA connect for sensor connection *3	Dimensions(cm) 21*20*4.1 Weight: IRW-489: 0.8KG IRW-469: 1.5KG



## MICROPHONE SPECIFICATIONS

IRW-89M	IRT-89	AT-101(NiMH)/AT-8(Li)
Carrier Frequency	depends	Carrier Frequency 2.08/2.54MHz
Current Consumption	230mA	Current CSP 230mA
Mic Unit	Dynamic	Built-in Mic uni-directional
Weight	253g	Input mic jack3.5mm
Battery	NiMH	Weight 71g(w/o batt)
Recharge	Charger Stand	Battery 2500mANiMH or Li-polymer
		Functions Volume control
	Functions Recharge	USB/ Charger Satnd
		Mute button
		Volume control
		Recharge USB/Wall charger

AllsWell Electronics Co., Ltd @ all rights reserved  
**亨優電子股份有限公司**  
**AllsWell Electronics**

Tel:8867-321-0227  
 Fax:8867-321-0228  
 Email: [allswell.fb@gmail.com](mailto:allswell.fb@gmail.com)  
 (find us on facebook, too)  
 Website: [www.allswell.com.tw](http://www.allswell.com.tw)

